

Quick Guide for Installing Conexant MonoPack-TAM Modem Driver

The CD includes below:

1. \Manual\ Modem manual.
2. \Rwmpci95\ Modem Driver for Windows 95/98.
3. \Rwmpci95\ Modem Driver for Windows NT4.0.
4. \Acrobat\ Acrobat reader.
5. Run "Setup.exe" or "Sv\Picshell.exe" from CD root directory to install SuperVoice or other software.

Quick software installation

Power on your computer and modem, then start Windows 95/98.

Windows 95/98 will detect the modem automatically.

1. Windows 95 B (OSR2):

- 1.1 Please insert the driver CD supplied and click "Next". The message of "PCI Communication Device" will appear. However, it may vary with the type of the mother board.
- 1.2 Windows will find the updated driver for "Conexant PCI Modem Enumerator", then click "Finish".
- 1.3 Click "OK".
- 1.4 Please type D:\RWMPCI95 ("D" is the letter of CD-ROM drive) and click "OK" to find the location of the modem driver and finish the driver installation.

2. Windows 98:

- 2.1 Please insert the driver CD supplied then click "Next". The message of "PCI Communication Device" will appear. However, it may vary with the type of your mother board.
- 2.2 Select "Search for the best driver for your device (Recommended)" and click "Next".

- 2.3 Select Specify a location and type "D:\Rwmpci95" ("D" is the letter of CD-ROM drive) and click "Next".
- 2.4 Windows will find the driver for "Conexant PCI Modem Enumerator", then click "Next".
- 2.5 Click "Finish" to end this installation procedure.

3. Selecting country code

- 3.1 Please go to "Start>Settings>Control Panel", double-click on "System" icon.
- 3.2 Click on "Device Manager" button, select "Conexant HCF 56K Data Fax RTAD PCI Modem" then click "Properties".
- 3.3 Click "Country Select" to select your country from the list and click "Apply". Then click "OK" to end this procedure.

4. Windows NT 4.0

- 4.1 Please insert the CD supplied. Then click "Start \ Run" on the desktop and use "Browse" to open the file of D:\RWMPCI95\SETUP.EXE. (D is the letter of CD-ROM drive)
- 4.2 Click "Next".
- 4.3 Click "Next".
- 4.4 The message of "The modem driver was installed successfully" will appear, then click "Finish". Note: You must restart your computer to enable the modem driver.
- 4.5 To select your country, please click "Start \Setting \Control Panel" on the desktop and double-click on the "HCF Modem Country Select" icon.
- 4.6 Select your country and click "OK".